- 1. Create a free Zello account which you will use for the gateway or use existing.
- 2. Add the account to one or more channels eg: 001english-eu.ddns.net
- 3. In the list of contacts select those channels (hold Ctrl to select multiple), then use menu Tools > Create group... Enter "**Zello Gateway**" as group name and click OK. You must use that group name exactly.
- 4. Exit Zello app using Menu > Exit.

(VERY IMPORTANT, MUST USE MENU AND EXIT!!!)

5. Locate **Zello.config** file. It's normally can be found in Zello folder:

## C:\Users\YOUR USER NAME HERE\AppData\Roaming\ZelloDesktop

- 6. Open the file in any text editor (eg Notepad), locate attribute named **SetGatewayMode** and change its value to **true**. (Delete false and replace with the word true)
- 7. Save the changed file.
- 8. Start Zello app. Now it will start in radio gateway mode and you can proceed to configuration of the gateway options under Tools > Options > Radio

Zello options		
	Radio	
Interface	TX (PC to Radio) RX (Radio to P(	5)
	Ovox	
Audio	Wake up sequence length (ms)	100 🔹
0	COM-port	
Consistion	Device	сомз ~
Connection	Signal	RTS 🗸 High 🗸
Ļ	CM108 HID	
VOX	Device	<unavailable></unavailable>
9	Signal	GPIO1 High
Radio		Harrison Harrison
0		
+S		
Local history		
		OK Cancel Apply

	Radio	
Interface	TX (PC to Radio) RX (Ra	dio to PC)
	● VOX	
Audio	VOX settings	
0	○ COM-port	
Connection	Device	COM4
	Signal	CTS High
Ŷ	CM108 HID	
VOX	Device	<ur><li><unavailable></unavailable></li></ur>
6	Signal	GPIQ1 High
Radio		
Ð	1	
Local history		

